





FI		A T	-11			-
_	-	Δ		ĸ	_	•

99 min timer / Child Lock / 5 Booster / Keep Warm / Pause Function

9 level power setting

Individual residual heat indicator

2-8 hours - automatic safety switch off

Slide touch

## **TECHNICAL DETAILS**

- 1. Induction (Heating element)
- 2. Power cord: 47 1/4" without plug
- 3. Voltage / Frequency: 240v /60Hz
- 4. Certification: ETL, RoHS, FCC
- 5. Amperage: 38.75A

## PRODUCT DIMENSIONS

- 1. Product Size (inch) (W\*D\*H): 36" 21" 2 1/4"
- 2. Cut out Size (inch) (W\*D): 33 7/8" 9 5/16"
- 3. Carton Size (inch) (W\*D\*H): 40 3/8" 27" 6 7/8"
- 4. Product Net/Gross weight (lbs): 28.66 / 36.38

## **FEATURES & BENEFITS**

- → 5 Elements The cooktop's total output power is 9,300W. Comes with one 11-inch cooking zone with 3,700W power boost mode, two 9-inch cooking zone with 2,100W boost mode and two 7-inch cooking zone with 1,500W boost mode to cover your cooking needs.
- 9 Power Levels So you can simmer a sauce or crank up the heat for a caramelized sear—now that's control
- **Power Boost** The cooktop elements offer a power boost adjustment so you get to your desired temperature fast
- Touch Controls Digital LED displays are touch and slide controlled and easy-to-read for the whole family and spills and grease can easily wipe away
- Residual Heat Indicators and Lock This cooktop also features a Residual Heat Indicator and Child Lock so that you and your kiddos don't burn your hands
- → Automatic Safety Shut-Off The unit will auto turn-off without a cooking pot present after 2-8 hours of non-operation-safety first. depending on power level. See the graph below for power levels and time.

Power Level	LV. 1-3	LV. 4-6	LV. 7-9
Shut Off	8 hours	4 hours	2 hours

ELEMENT PERFORMANCE				
Number of Elements	5			
1. Left Rear zone: 7"	1200/1500W			
2. Left Front zone: 9"	1800/2100W			
3. Right Rear zone: 9"	1800/2100W			
4. Right Front zone: 7"	1200/1500W			
5. Central zone: 11"	2300/3700W			
Max Output	8300W			

**WARRANTY: 2 YEARS ON PARTS AND LABOR** 



